



204.95 EUR

incl. 19% VAT, plus shipping

- INTEL® Pine Trail-D Processor D525+ ICH8M Chipset
- Support 1 \* DDR3 667/800MHz Single CH up to 2GB
- 3. Support 1 \* Serial ATAII (3Gb/s) Devices
- 1 \* 18 bits Single Channel LVDS header
- Supports 4 \* Realtek RT8111EVL Gigabit LAN
- Provides 2 \* Mini PCI-E socket (one support mSATA card)
- Provides 1 \* CF card socket (can support both CF card & CF SATA card)
- Provides 1 \* SIM card socket (optional)
- Provides front I/O card for 4 \* LAN LED indicators
- Support CPU Smart FAN
- Compliance with ErP standard
- 148 x 102mm 3.5" SBC Form Factor

<b>CPU</b>	INTEL® Pine Trail-D Processor D525 (1.86GHz)
<b>Chipset</b>	INTEL® ICH8M Express chipset
<b>Memory</b>	1 * DDR3 667/800MHz Single CH SO-DIMM up to 2GB
<b>Expansion Slots</b>	2 * full size Mini PCI-E

<b>Storage</b>	1 * Serial ATAll 3Gb/s connectors 1 * mSATA socket (Share with one of Mini PCI-E socket)
<b>Audio</b>	N/A
<b>Ethernet LAN</b>	4 * RTL8111E PCI-EVL Gigabit LAN
<b>USB</b>	Embedded 6 * USB 2.0/1.1
<b>LVDS</b>	Onboard 1 * 18-bits Single CH LVDS connectors
<b>Rear Panel I / O</b>	2 * USB 2.0/1.1 ports 1 * COM port 4 * RJ-45 ports 1 * 12V DC-IN JACK
<b>Internal I / O</b>	2 * USB 2.0 header for 4 * USB 2.0 ports 1 * VGA header 1 * COM header (COM2 for RS232/422/485) 1 * GPIO header 1 * CIR header System/Chassis/NB Fan Connectors 1 * CF card socket (can support both CF card & CF SATA card) DIY switch x2 (reset & power button)
<b>BIOS</b>	AMI 8MB DIP Flash ROM
<b>Form Factor</b>	3.5" SBC form factor (148mmx102mm)
<b>Certificate</b>	CE,FCC,RoHS,ERP
<b>Functional</b>	Networking Appliance
<b>Temperature</b>	Operating within 0~60 centigrade Storage within -20-85 centigrade
<b>Product Accessories</b>	- Front I/O card - Front panel cable

- NIC LED cable
- USB cable
- Manual
- CD
- 1x SATA cable
- SATA power cable