



79.95 EUR

incl. 19% VAT, plus shipping

- **Intel Celeron 1007U !**
- **Dual Gigabit LAN !**
- **WinXP, Win7, Win 8 !**



- GIGABYTE Dual UEFI BIOS
- All new design of Ultra Durable 4 classic
- Industry's Leading All Solid Capacitor Design
- Dual LAN for networking flexibility
- HDMI interface for smoother HD video playback
- GIGABYTE On/Off Charge™ for USB devices
- Windows 8 ready

#### CPU

1. Built in with an Intel® Dual-core Celeron® 1007U processor (1.5 GHz)  
\* Do not disassemble the onboard CPU/chipset and the heatsinks/fan by your own, to avoid damage to these components.
2. 2 MB L3 cache

#### Chipset

1. Intel® NM70 Chipset

## Memory

1. 2 x 1.5V DDR3 DIMM sockets supporting up to 16 GB of system memory
  - \* Due to a Windows 32-bit operating system limitation, when more than 4 GB of system memory is installed, the actual memory size displayed will be less than the memory installed.
2. Dual channel memory architecture
3. Support for DDR3 1333/1066 MHz memory modules

(Please refer "Memory Support List" for more information.)

## Onboard Graphics

Integrated Graphics Processor:

1. 1 x D-Sub port
2. 1 x HDMI port, supporting a maximum resolution of 1920x1200
  - \* Support for HDMI 1.4 version.
3. Maximum shared memory of 1 GB

## Audio

1. Realtek ALC887 codec
2. High Definition Audio
3. 2/4/5.1/7.1-channel
  - \* To configure 7.1-channel audio, you have to use an HD front panel audio module and enable the multi-channel audio feature through the audio driver.

## LAN

1. 2 x Realtek GbE LAN chips (10/100/1000 Mbit)

## Expansion Slots

1. 1 x PCI slot

## Storage Interface

Chipset:

1. 1 x SATA 6Gb/s connector (SATA3 0) supporting up to 1 SATA 6Gb/s device
2. 2 x SATA 3Gb/s connectors (SATA2 1~2) supporting up to 2 SATA 3Gb/s devices
3. 1 x eSATA 3Gb/s connector on the back panel supporting up to 1 SATA 3Gb/s device

JMicron JMB368 chip:

1. 1 x IDE connector supporting ATA-133/100/66/33 and up to 2 IDE devices

## USB

Chipset:

1. Up to 8 USB 2.0/1.1 ports (4 ports on the back panel, 4 ports available through the front panel USB headers)

## Internal I/O Connectors

1. 1 x 24-pin ATX main power connector
2. 1 x 4-pin ATX 12V power connector
3. 1 x IDE connector
4. 1 x SATA 6Gb/s connector
5. 2 x SATA 3Gb/s connectors
6. 1 x CPU fan header
7. 1 x system fan header
8. 1 x front panel header
9. 1 x front panel audio header
10. 2 x USB 2.0/1.1 headers
11. 1 x parallel port header
12. 1 x serial port header
13. 1 x Clear CMOS jumper
14. 1 x chassis intrusion header

## Back Panel Connectors

1. 1 x PS/2 keyboard port
2. 1 x PS/2 mouse port
3. 1 x D-Sub port
4. 1 x serial port
5. 1 x HDMI port
6. 4 x USB 2.0/1.1 ports
7. 1 x eSATA 3Gb/s connector
8. 2 x RJ-45 ports
9. 3 x audio jacks (Line In/Line Out/Microphone)

## I/O Controller

1. iTE I/O Controller Chip

## H/W Monitoring

1. System voltage detection
2. CPU/System temperature detection
3. CPU/System fan speed detection
4. System fan speed control

\* Whether the system fan speed control function is supported will depend on the BIOS you install.

## BIOS

1. 2 x 32 Mbit flash
2. Use of licensed AMI EFI BIOS
3. Support for DualBIOS™
4. PnP 1.0a, DMI 2.0, SM BIOS 2.6, ACPI 2.0a

## Unique Features

1. Support for @BIOS
2. Support for Q-Flash
3. Support for Xpress Install
4. Support for Xpress Recovery2
5. Support for EasyTune 6
  - \* Available functions in EasyTune 6 may differ by motherboard model.
6. Support for Smart Recovery 2
7. Support for Auto Green
8. Support for ON/OFF Charge

## Bundle Software

1. Norton Internet Security (OEM version)
2. Intel<sup>®</sup> Smart Connect Technology

## Operating System

1. Support for Microsoft Windows 8/7/XP

## Form Factor

1. Mini-ITX Form Factor; 17.0cm x 17.0cm

## Remark

1. Due to different Linux support condition provided by chipset vendors, please download the driver from chipset vendors' website or 3rd party website.
2. Most hardware/software vendors may no longer offer drivers to support Windows SP1/SP2. If drivers are available from the vendors, we will update them on our website.